

CHG 863-35

35-Unit Briefcase Charger for T2863, R2863

This briefcase style charger will charge up to 35 Williams Sound 863MHz transmitters or receivers at the same time. It also provides convenient storage and/or transport.



CHG 863-35 Specification Data

Dimensions:	56.2 cm L x 38.1 cm W x 12.9 cm H (22-1/8"L x 15"W x 5-1/16"H) Dimensions include handle and power switch.
Shipping Weight:	5.28 kg (11.65 lbs)
Enclosure:	Aluminum, Silver Color
Power:	100-240VAC, 50-60Hz. Use line cord appropriate for country of use.
Fuse:	Use F5AL250V or equivalent.
Capacity:	Up to 35 Units can charge simultaneously.
Charging Time:	Up to 5 hours per unit
Indicators:	Charger: Power Switch glows indicating charger is on. T2863 or R2863: Charging light on top of unit Flashes once per second (Slow) = Charging, Flashes Fast = Incorrect Battery Type, On Steady = Charged
Warranty:	2 years
Approvals:	RoHS

Domestic Sales

Williams Sound
10300 Valley View Rd.
Eden Prairie, MN 55344
Ph: 800-328-6190 / 952-943-2252
FAX: 952-943-2174
Email: info@williamssound.com
Web: www.williamssound.com

International Sales

International Sales Department
Williams Sound
10300 Valley View Rd.
Eden Prairie, MN 55344 USA
Phone: +1 952 943 2252
Fax: +1 952 943 2174
Email: info-intl@williamssound.com
Web: www.williamssound.com



WILLIAMS SOUND®
HELPING PEOPLE HEAR

800.843.3544 / info@williamssound.com / www.williamssound.com